

## RCP04 Plug-in socket radio bell

The RCP04 plug-in radio bell socket emits a visual and acoustic signal. When the signal of a programmed Easywave radio transmitter is detected, the set ringtone sounds.

Three tunes combined with an integrated flashing light are available to choose from. The ringtone duration can be set to between seven seconds and one minute.

In total, 32 transmitters can be programmed, each with its own selected combination of ringtone, ringtone duration and flashing light.

**Energy efficient:** The RCP04 consumes only 0.3 W in standby mode.




RCP04E5001-11-01K

### Technical specifications

Coding	Easywave Up to 32 transmitters can be programmed.
Frequency	868.30 MHz
Channels	1
Power supply	230 V AC, 50 Hz
Power consumption	0.3 W standby
Volume	at a distance of 30 cm: 75 dB (low), 82 dB (high)
Outputs	power outlet: country-specific plug system
Maximum contact load	mains voltage (not switchable): D/A/NL/S/N und CH 10 A / 230 V AC GB 13 A / 230 V AC F/B/PL 16 A / 230 V AC
Operating temperature	-20 °C to +35 °C
Dimensions	50 x 120 x 75 mm
Color	white similar to RAL 9003

### Plug system



### Scope of delivery

- Plug-in socket radio bell
- Operating manual

### Models

Product numbers	Description	Plug system
RCP04E5001-11-01K	Plug-in socket radio bell 1-channel, white	D/A/NL/S/N
RCP04E5001-12-01K	Plug-in socket radio bell 1-channel, white	GB
RCP04E5001-14-01K	Plug-in socket radio bell 1-channel, white	F/B/PL
RCP04E5001-15-01K	Plug-in socket radio bell 1-channel, white	CH