# 3CX Phone Configuration Guides



Register 3CX Phone on Windows

Register 3CX Phone on Android or iOS devices

3CX Phone can be used with MyPBX. It means that you can register MyPBX extension on 3CX Phone of your Windows, Android or iOS devices. Please follow the steps to register your extension.

# **Register 3CX Phone on Windows**

Step1. Download (<u>http://www.3cx.com/downloads/3CXPhone6.msi</u>) and install 3CX Phone on your Windows PC and launch 3CX Phone. Click 'Create a profile' on the popup window and click 'New' to add new SIP accounts.







Step 2. Enter MyPBX extension register information and click 'OK'. The status will show 'on hook' on 3CX Phone (Please make sure your device Wi-Fi is connected).

Account name:	Rela					
Caller ID:	Rela					
Credentials		-				
Enter your SIP account creden	Enter your SIP account credentials					
Extension:	554					
ID:	554					
Password:	********	J				
My location	My location					
Specify the IP of your PBX/SIP	Specify the IP of your PBX/SIP server					
I am in the office - local IP	192.168.4.141	of PBX				
C I am out of the office - exte	ernal IP	of PBX				
Use 3CX Tunnel						
Eliminates firewall configuration. Requires 3CX Phone System for Windows						
Local IP of remote PBX:	192.168.4.141					
Tunnel password:	*** Port: 5090					
Use Outbound Proxy server						
Required by some VoIP Providers. Specify IP or name.						
Perform provisioning from following URL:						
http://						
Advanced settings	СК	Cancel				

Account numer		Rela		
Caller ID:		Rela		_
Credentials				
Enter your SIP account crede	entials			
Extension:		554		
ID:		554		
Password:		******		
My location				
Specify the IP of your PBX/SI	P server			
C I am in the office - local IP		192.168.4.141		of PE
I am out of the office - ext	ternal IP	yeastar.com		of PE
Use 3CX Tunnel		2CV Phase C		
Use 3CX Tunnel Eliminates firewall configuration Windows	on. Requir	es 3CX Phone S	ystem for	r
Use 3CX Tunnel Eliminates firewall configuration Windows Local IP of remote PBX:	on. Requir	es 3CX Phone S	ystem for	r
Use 3CX Tunnel Eliminates firewall configuratio Windows Local IP of remote PBX: Tunnel password:	on. Requir 192.	res 3CX Phone S 168.4.141 Port:	ystem for	r
Use 3CX Tunnel Eliminates firewall configuratio Windows Local IP of remote PBX: Tunnel password:	on. Requir 192. *** er -	res 3CX Phone S 168.4.141 Port:	ystem for	r
Use 3CX Tunnel Elminates firewall configurati Windows Local IP of remote PBX: Tunnel password: Use Outbound Proxy serv Required by some VoIP Provin	on. Requir 192. *** er - ders. Spec	res 3CX Phone S 168.4.141 Port: cify IP or name.	ystem for 5090	r
Use 3CX Tunnel  Imnates firewall configurativ  Windows Local IP of remote PBX:  Tunnel password:  Use Outbound Proxy serv  Required by some VoIP Provi	on. Requir 192. *** er ders. Spec	tes 3CX Phone S 168.4.141 Port: cify IP or name.	stem for	r
Use 3CX Tunnel      Eliminates firewall configuratis Windows Local IP of remote PBX: Tunnel password:     Use Outbound Proxy serv Required by some VoIP Provi Perform provisioning from	on. Requir 192. *** er ders. Spec following	es 3CX Phone S 168.4.141 Port: cify IP or name.	stem for	r
Use SQX Tunnel Use SQX Tunnel Use SQX Tunnel porsense PBX: Use Outbound Proxy serve Required by some VoIP Provide Perform provisioning from https://	on. Requir 192. *** er ders. Spec following	es 3CX Phone S 168.4.141 Port: Cify IP or name.	stem for	r



Figure 3 Register locally

Figure 4 Register remotely

Figure 5 Register successfully

Account name & Caller ID: you can customize the fields.

## Credentials

Extensions: Fill in the extension number which you have created on MyPBX.

ID: The same as the extension number.

Password: Password you set for this extension on MyPBX.



### My Location

Choose 'I am in the office' and fill in MyPBX local IP here if you are registering locally. Choose 'I am out of the office' and fill in MyPBX public IP or domain if you are registering remotely. Please refer to this link for the settings of register MyPBX remote extensions: <u>http://www.yeastar.com/download/Register-To-MyPBX-Remotely.pdf</u>

## **Register 3CX Phone on Android or iOS devices**

Step1. Download (From App Store or Google Play) and install 3CX Phone on Android or iOS devices and launch 3CX Phone. Click 'Create a profile' on the popup window and enter in MyPBX extension register information(Please make sure your device Wi-Fi is connected).



Figure 6

iPod 奈	19:16	e 🗖
	Settings	Done
Name:		Rela
Display name	e:	Rela
Credentials		
User:		554
ID:		554
Password:	•••	•••••
Server settin	gs	
Use as		In Office 🔉
Local PBX IP	<b>:</b> 192	.169.4.141

Pod	15:43		(Et 🗖	
	Setting	gs	Done	
Display na	ame:		Rela	
Credentia	ls			
User:			554	
ID:			554	
Password	:	••••		
Server set	tings			
Use as	Out Of	Office Tu	unnel 🔉	
Local PBX IP:				
External F	BX IP:	yeas	tar.com	
DRY nort			5060	

Figure 7 Register locally

Figure 8 Register remotely

Name & Display name: you can customize the fields.

#### Credentials

User: Fill in the extension number which you have created on MyPBX.

ID: The same as the extension number.

Password: Password you set for this extension on MyPBX.

#### Server settings

Use as 'In Office' and fill in MyPBX local IP here if you are registering locally.

Use as 'Out Of Office Tunnel' and fill in MyPBX public IP or domain if you are registering remotely. Please refer to this link for the settings of register MyPBX remote extensions: <u>http://www.yeastar.com/download/Register-To-MyPBX-Remotely.pdf</u>

Step2. When done, the status will show 'on hook' on 3CX Phone. You can make and receive calls with 3CX Phone then.



## **3CX Phone Configuration Guides**



Figure 9 Register successfully



Figure 10 Receiving a call