

BELL-240 RX

2 0 S

WIRELESS RECEIVER

- 8 selectable melodies, volume adjustable
- Full area optical bell signal (flashing or continuous light) 3 colours selectable
- Function selector switch: Sound + light / Sound only / Light only
- Volume adjustable
- Range up to 200 metres (open field)
- Battery control LED
- Learning code coding to avoid interference with similar devices in your neighbourhood
- Expandable to up to 4 transmitters
- Expandable with several additional receivers
- Dimensions (LxWxH): 116 x 116 x 36 mm

UP TO 200m

Expandable with transmitters and receivers

OPTICAL **ACOUSTIC** ANNOUNCEMENT

8 **MELODIES**

OPTICAL BELL SIGNAL in 3 selectable colours



BELL-240 RX

	I L C II N I C A L D A I A	
MODEL	Bell-240 RX Receiver for Wireless Doorbell	Art no: 41143
SCOPE OF DELIVERY	1x Receiver	
DEVICE (L x W x H)	116 x 116 x 36 mm	
GIFTBOX	194 x 265 x 44 mm (L x W x H) • 315 g	
EXPORT BOX	20 pieces • 545 x 420 x 230 mm (L x W x H) • 7.3 kg	
POWER SUPPLY	4x AA battery (not included)	
RANGE	Up to 200 metres • Frequency: 434 MHz	
APPROVAL	European Union	
EAN CODE	4250109132553	

WWW.M-E.DE

RANGE