

NEW

# **BELL-280 RX**

O

4

# MOBILE

# WIRELESS RECEIVER

- Receiver for mains operation in the charging cradle or mobile use with long-life Li-lon rechargeable battery
- Inductive charging cradle for contactless charging of receiver
- Optical announcement by illuminated ring 3 colours selectable
- Function selector switch: Sound + light / Sound only / Light only

me

- 8 selectable melodies in excellent sound quality
- Multi-level volume adjustment
- Range up to 150 metres (open field)
- Learning code coding to avoid interference with similar devices in your neighbourhood
- Expandable with max. 4 transmitters
- Expandable with several additional receivers
- Dimensions receiver (LxWxH): 63 x 130 x 30 mm



UP TO 150m RANGE

Expandable with transmitters and receivers

OPTICAL

ACOUSTIC

BELL SIGNAL

**8** MELODIES

RECEIVER
LI-ION
BATTERY

OPTICAL
BELL SIGNAL
3 colours selectable





RED GREEN BLUI

MAINS CHARGING CRADLE
NON-CONTACT CHARGING





## DELL-280 RX

### TECHNICAL DAT

|  | DELL-ZOV KX        | IECHNICAL DAIA  |
|--|--------------------|---|
|  | MODEL              | Bell-280 RX Wireless receiver Art no: 41151                                 |
|  | SCOPE OF DELIVERY  | 1x mobile receiver, 1x charging cradle                                      |
|  | DEVICE (L x W x H) | Receiver: 63 x 130 x 30 mm • Charging cradle: 68 x 110 x 26 mm without plug |
|  | GIFTBOX            | 186 x 265 x 72 mm (LxWxH) • 325 g   |
|  | EXPORT BOX         | 20 pieces • 475 x 320 x 495 mm (LxWxH) • 7.6 kg                             |
|  | POWER SUPPLY       | 230V / 50 Hz in charging cradle or with built-in LiPo battery               |
|  | RANGE              | Up to 150 metres • Frequency: 434 MHz                                       |
|  | APPROVAL           | European Union  |
|  | EAN CODE           | 4250109132638   |